COMMSCOPE

R850

Indoor Wi-Fi 6 8x8:8 Access Point with 5.9 Gbps Data Rate



Benefits

Connect More Devices Simultaneously

Improve device performance, by enabling more simultaneous device connections with built-in 12 spatial streams (8x8:8 in 5GHz, 4x4:4 in 2.4GHz), MU-MIMO and OFDMA technology.

Ultra-High-Density Performance

Provides exceptional end-user experience within stadiums, large public venues, convention centers and school auditoriums with the RUCKUS Ultra-High-Density Technology Suite.

Enhanced Security

Supports the latest Wi-Fi security standard, WPA3, for enhanced protection from man-in-the-middle attacks in the most secure way.

Multi-Gigabit Access Speeds

Optimized multi-gigabit Wi-Fi performance delivered using built-in 5GbE/2.5GbE Ethernet ports to connect to multi-gigabit switches.

Device Management Options

Manage the R850 with cloud, on premise physical/ virtual appliances and control auto-provisioning for faster deployment and seamless firmware upgrades.

Better Mesh Networking

Minimize complexity by reducing expensive cabling with SmartMesh that dynamically creates self-forming, self-healing mesh networks.

Converged Access Point

Eliminate siloed wireless networks with a unified platform that augments Wi-Fi with onboard BLE & Zigbee radios with the option to integrate other wireless technologies via the USB port.

More Than Wi-Fi

Support services beyond Wi-Fi with <u>RUCKUS loT</u> <u>Suite</u>, <u>Cloudpath</u> security and onboarding software, <u>SPOT</u> Wi-Fi locationing engine, and <u>RUCKUS analytics</u>.

The R850 is based on the latest Wi-Fi standard, Wi-Fi 6, which bridges the performance gap from 'gigabit' Wi-Fi to 'multi-gigabit' Wi-Fi in support of the insatiable demand for better and faster Wi-Fi.

The RUCKUS R850 is our highest capacity dual-band, dual-concurrent Wi-Fi 6 access point (AP) that supports 12 spatial streams (8x8:8 in 5GHz, 4x4:4 in 2.4GHz). The R850, with OFDMA, TWT and MU-MIMO capabilities, efficiently manages up to 1,024 client connections with increased capacity, improved coverage and performance in ultra-high dense environments. Furthermore, a 5 Gbps multi-gigabit Ethernet port mitigates backhaul capacity bottlenecks.

Additionally, the R850 is IoT- and LTE-ready, and supports wireless standards beyond Wi-Fi in combination with the RUCKUS IoT Suite and our CBRS/OpenG modules.

The R850 addresses the increasing client demands in transit hubs, auditoriums, stadiums, conference centers, and other highly trafficked indoor spaces. It is the perfect choice for data-intensive streaming multimedia applications like 4K video transmissions, while supporting latency sensitive voice and data applications with stringent quality-of-service requirements.

The R850 when paired with the RUCKUS Ultra-High-Density Technology Suite found only in the RUCKUS Wi-Fi portfolio, dramatically improves network performance through a combination of patented wireless innovations and learning algorithms that includes:

- Airtime Decongestion: Increases average network throughput in heavily congested environments
- Transient Client Management: Reduces interference traffic from unconnected Wi-Fi devices
- BeamFlex Antennas: Extended coverage and optimized throughput with patented multidirectional antennas and radio patterns

Whether you're deploying ten or ten thousand APs, the R850 is also easy to manage through our collection of on-premises or cloud-based management options.

Indoor Wi-Fi 6 8x8:8 Access Point with 5.9 Gbps Data Rate

Access Point Antenna Pattern

RUCKUS' BeamFlex+ adaptive antennas allow the R850 AP to dynamically choose among a host of antenna patterns (over 4,000 possible combinations) in real-time to establish the best possible connection with every device. This leads to:

- Better Wi-Fi coverage
- Reduced RF interference

Traditional omni-directional antennas, found in generic access points, oversaturate the environment by needlessly radiating RF signals in all directions. In contrast, the RUCKUS BeamFlex+ adaptive antenna directs the radio signals per-device on a packet by-packet basis to optimize Wi-Fi coverage and capacity in real-time to support high device density environments. BeamFlex+ operates without the need for device feedback and hence can benefit even devices using legacy standards.

Figure 1. Example of BeamFlex+ pattern




Figure 2. R850 2.4GHz Azimuth Antenna Patterns



Figure 3. R850 5GHz Azimuth Antenna Patterns



Figure 4. R850 2.4GHz Elevation Antenna Patterns





Figure 5. R850 5GHz Elevation Antenna Patterns



Note: The outer trace represents the composite RF footprint of all possible BeamFlex+ antenna patterns, while the inner trace represents one BeamFlex+ antenna pattern within the composite outer trace.

Indoor Wi-Fi 6 8x8:8 Access Point with 5.9 Gbps Data Rate

WI-FI	
Wi-Fi Standards	IEEE 802.11a/b/g/n/ac/ax
Supported Rates	 802.11ax: 4 to 4800 Mbps 802.11ac: 6.5 to 3467 Mbps 802.11n: 6.5 to 600 Mbps 802.11a/g: 6 to 54 Mbps 802.11b: 1 to 11 Mbps
Supported Channels	• 2.4GHz: 1-13 • 5GHz: 36-64, 100-144, 149-165
MIMO	8x8 MU-MIMO 8x8 SU-MIMO
Spatial Streams	8 MU-MIMO 8 SU-MIMO
Radio Chains and Streams	• 8x8:8
Channelization	• 20, 40, 80MHz
Modulation	OFDMA (up to 1024-QAM)
Security	WPA-PSK, WPA-TKIP, WPA2 AES, 802.11i, Dynamic PSK WIPS/WIDS
Other Wi-Fi Features	WMM, Power Save, TxBF, LDPC, STBC, 802.11r/k/vHotspot Hotspot 2.0 Captive Portal WISPr

RF	
Antenna Type	BeamFlex+ Adaptive Antennas with 4000+ unique antenna patterns Horiziontal and Vertical polarization (PD-MRC)
Antenna Gain (max)	• Up to 2 dBi
Frequency Bands	 2.4 - 2.484 GHz 5.17 - 5.33 GHZ 5.49 - 5.71 GHz 5.735 - 5.835 GHz

2.4GHZ R	CEIVE SENS	SITIVITY					
НТ	HT20 HT40			VH	T20	VHT40	
MCS0	MCS7	MCS0	MCS7	MCS0	MCS7	MCS0	MCS7
-91	-73	-88	-70	-91	-73	-88	-70
	HE20				HE	40	
MCS0	MCS7	MCS9	MCS11	MCS0	MCS7	MCS9	MCS11
-91	-73	-68	-62	-88	-70	-65	-59

5GHZ	RECEIVE	SENSIT	IVITY								
	VH	Т20			VHT40			VHT80			
MCS0	MCS7	MCS8	MCS9	MCS0	MCS7	MCS8	MCS9	MCS0	MCS7	MCS8	MCS9
-91	-72	-69	_	-88	-69	_	-65	-85	-66	_	-62
HE20 HE40					HE40				HE	80	
MCS0	MCS7	MCS9	MCS11	MCS0	MCS7	MCS9	MCS11	MCS0	MCS7	MCS9	MCS11
-91	-72	-68	-62	-88	-69	-65	-59	-85	-66	-62	-56

2.4GHZ TX POWER TARGET (PER CHAIN)				
Rate	Pout (dBm) - Full Power	Pout (dBm) - 802.3at		
MCS0 HT20	20	20		
MCS7 HT20	16	16		
MCS8 VHT20	15	15		
MCS9 VHT40	14	14		
MCS11 HE40	12	12		

5GHZ TX POWER TARGET (PER CHAIN)				
Rate	Pout (dBm) - Full Power	Pout (dBm) - 802.3at		
MCS0 VHT20	22	22		
MCS7 VHT40, VHT80	16.5	16.5		
MCS9 VHT40, VHT80	15	15		
MCS11 HE20, HE40, HE80	12.5	12.5		

PERFORMANCE AND CAPACITY		
Peak PHY Rates	2.4GHz: 1.148 Gbps (11ax) 5GHz: 4.8 Gbps (11ax)	
Client Capacity	Up to 1024 clients per AP	
Simultaneous VoIP Clients	Up to 60 per AP	
SSID	Up to 16 per radio	

RUCKUS RADIO MANAGEMENT			
Antenna Optimization	BeamFlex+ PD-MRC		
Wi-Fi Channel Management	ChannelFly		
Client Density Management	Band Balancing Client Load Balancing Airtime Fairness Airtime-based WLAN Prioritization		
Queuing & Scheduling	SmartCast		
Mobility	SmartRoam		
Diagnostic Tools	Spectrum Analysis SpeedFlex		
High Density Deployments (RF Innovations)	Perpacket Adaptive Power Adaptive Wi-Fi Cell Size Transient Client Management Airtime Decongestion		

Indoor Wi-Fi 6 8x8:8 Access Point with 5.9 Gbps Data Rate

NETWORKING	
Controller Platform Support	SmartZoneZDStandaloneCloud
Mesh	SmartMesh™ wireless meshing technology
IP	• IPv4, IPv6
VLAN	802.1Q BSSID-based (16 BSSIDs / radio) Port-based Dynamic, per user based on RADIUS
802.1x	Wired & wireless Authenticator & Supplicant
Tunnel	RuckusGRE, SoftGRE
Policy Management Tools	Application Recognition and ControlAccess Control ListsDevice Fingerprinting
IoT Capable	Yes

OTHER RADIO TECHNOLOGIE	5
IoT	BLE, Zigbee

PHYSICAL INTERFACES	
Ethernet	1x 1/2.5/5 Gbps port, RJ-451x 10/100/1000 Mbps port, RJ-45
USB	1 USB 2.0 port, Type A

PHYSICAL CHARACTERISTICS		
Physical Size	• 22.19 x 24.96 x 6 cm • 8.74 x 9.83 x 2.36 in.	
Weight	• 1.53 kg • 3.37 lbs	
Mounting	Wall, Acoustic ceiling, Desk Secure Bracket (sold separately)	
Physical Security	Hidden Latching Mechanism	
Operating Temperature	• -0C (32F) to 50°C (122°F)	
Operating Humidity	Up to 95%, non-condensing	

POWER CONS	POWER CONSUMPTION		
Mode	Power Consumption	System Configuration	Wi-Fi Radios
DC Power, PoH, uPoE (Idle)	16.1W	5Gbps Ethernet Enabled 1Gbps Ethernet Enabled USB Enabled (3W) Zigbee/BLE Enabled (0.5W)	2.4GHz (4x4) Enabled 5GHz (8x8) Enabled (<i>No Clients Associated</i>)
DC Power, PoH, uPoE (Max)	31.0W	5Gbps Ethernet Enabled 1Gbps Ethernet Enabled USB Enabled (3W) Zigbee/BLE Enabled (0.5W)	2.4GHz (4x4) Tx 20 dBm 5GHz (8x8) Tx 22 dBm
802.3at (Mode 0)*	23.8W	5Gbps Ethernet Enabled1Gbps Ethernet EnabledUSB Enabled (3W)Zigbee/BLE Disabled	2.4GHz (4x4) Tx 20 dBm 5GHz (4x4) Tx 22 dBm
802.3at (Mode 1)*	25.31W	 5Gbps Ethernet Enabled 1Gbps Ethernet Disabled USB Disabled (3W) Zigbee/BLE Disabled 	2.4GHz (4x4) Tx 20 dBm 5GHz (8x8) Tx 20 dBm
802.3af (Not re- commended)	12.4W	 5Gbps & 1Gbps Ethernet enabled USB Disabled Zigbee/BLE Disabled	2.4GHz disabled 5GHz disabled

^{*}For 802.3at Mode 0/Mode 1 details - please refer to R850 AP Release Notes.

CERTIFICATIONS AND COMPL	COMPLIANCE	
Wi-Fi Alliance	 Wi-Fi CERTIFIED™ a, b, g, n, ac, ax Passpoint® Vantage 	
Standards Compliance	 EN 60950-1 Safety EN 60601-1-2 Medical EN 61000-4-2/3/5 Immunity EN 50121-1 Railway EMC EN 50121-4 Railway Immunity IEC 61373 Railway Shock & Vibration EN 62311 Human Safety/RF Exposure UL 2043 Plenum WEEE & ROHS ISTA 2A Transportation 	

SOFTWARE AND SERVICES	are and services	
Location Based Services	• SPoT	
Network Analytics	SmartCell Insight (SCI)	
Security and Policy	Cloudpath	
IoT	Ruckus IoT Suite	

Indoor Wi-Fi 6 8x8:8 Access Point with 5.9 Gbps Data Rate

ORDERING INFORMATION	IG INFORMATION	
901-R850-XX00	R850 dual-band (5GHz and 2.4GHz concurrent) 802.11ax wireless access point, Ultra-High Density performance, 12 spatial streams, adaptive antennas, PoE support. Includes adjustable acoustic drop ceiling bracket. Two Ethernet ports with 1GbE and 5Gbe. Does not include power adaptor	

PLEASE NOTE: When ordering Indoor APs, you must specify the destination region by indicating -US, -VWW, or -Z2 instead of XX. When ordering PoE injectors or power supplies, you must specify the destination region by indicating -US, -EU, -AU, -BR, -CN, -IN, -JP, -KR, -SA, -UK, or -UN instead of -XX

For access points, -Z2 applies to the following countries: Algeria, Egypt, Israel, Morocco, Tunisia, and Vietnam.

OPTIONAL ACCESSORIES	L ACCESSORIES	
902-0180-XX00	PoE Injector (60W)	
902-1170-XX00	• Power Supply (48V, 0.75A, 36W)	
902-0120-0000	Spare, Accessory Mounting Bracket	

PLEASE NOTE: When ordering Indoor APs, you must specify the destination region by indicating -US, or -Winstead of XX. When ordering PoE injectors or power supplies, you must specify the destination region by indicating -US, -EU, -AU, -BR, -CN, -IN, -JP, -KR, -SA, -UK, or -UN instead of -XX.

CommScope pushes the boundaries of communications technology with game-changing ideas and ground-breaking discoveries that spark profound human achievement. We collaborate with our customers and partners to design, create and build the world's most advanced networks. It is our passion and commitment to identify the next opportunity and realize a better tomorrow. Discover more at commscope.com

COMMSCOPE®

commscope.com

Visit our website or contact your local CommScope representative for more information.

© 2020 CommScope, Inc. All rights reserved.

Unless otherwise noted, all trademarks identified by * or ™ are registered trademarks, respectively, of CommScope, Inc. This document is for planning purposes only and is not intended to modify or supplement any specifications or warranties relating to CommScope products or services. CommScope is committed to the highest standards of business integrity and environmental sustainability with a number of CommScope's facilities across the globe certified in accordance with international standards, including ISO 9001, TL 9000, and ISO 14001.

Further information regarding CommScope's commitment can be found at www.commscope.com/About-Us/Corporate-Responsibility-and-Sustainability