



## T03 Line Sequence Converter

T03 Line Sequence Converter is plug-and-play and easy to deploy.

Fanvil IP Phone can support 03 line sequence headset by this accessory,, greatly improving the adaptability and flexibility.

### Highlights

- ☑ Compatible with Fanvil IP Phone
- ☑ Ease-of-use
- ☑ Plug and Play




### Product Specifications

- Cable length: 150mm  $\pm$  30mm
- Line sequence: From Q01 to Q03
- Interface: RJ9 Socket (4P4C) and RJ9 Plug (4P4C)
- Working Temperature: 0~45°C
- Working Humidity: 20~85%
- Color: Black


### Packaging information

- Gift Box Dimensions: 120 x 80mm
- N.W/PCS: 7.6 g
- G.W/PCS: 10 g

#### Q03 Line sequence (RJ9 Socket)



#### Q01 Line sequence (RJ9 Plug)



#### Q03 Line sequence (RJ9 Socket)

1. MIC+
2. Speaker-
3. Speaker+
4. MIC-

#### Q01 Line sequence (RJ9 Plug)

1. MIC-
2. Speaker-
3. Speaker+
4. MIC+

The above specifications may be updated in the future without prior notice. All hardware/software/physical features should be based on the final shipped products.  
For more information, please visit: [www.fanvil.com](http://www.fanvil.com)

